


## Article Information Sheet (AIS)

This Article Information Sheet (AIS) provides relevant battery information to retailers, consumers, OEMs and others users requesting a GHS-compliant SDS. Articles, such as batteries, are exempt from GHS SDS classification criteria. The GHS criteria is not designed or intended to be used to classify the physical, health and environmental hazards of an article. Branded consumer batteries are defined as electro-technical devices. The design, safety, manufacture, and qualification of branded consumer batteries follow ANSI and IEC battery standards. This document is based on principles set forth in the following hazard communication approaches: ANSI Z-400.1, GHS, JAMP AIS, IEC 62474, and ANSI C18.4M.

1. Document Information	
Document Name	Duracell Zinc Air Batteries (Hearing Aid Cells)
Document ID	AIS-ZA
Issue Date	16-Dec-15
Version	6.0
Preparer	Product Safety & Regulatory
Last Revision	1/18/2022
Information Contact	<a href="mailto:SDS@duracell.com">SDS@duracell.com</a>
2. Company Information	
NA Name & Address	Duracell US Operations, 14 Research Drive, Bethel, CT USA 06801. Duracell Batteries BV, Nijverheidslaan 7, 3200 Aarschot, Belgium. Duracell International Operations Sàrl, Rue du Pré-de-la-Bichette 1, CH-1202, Geneva, Switzerland.
Telephone	(203) 796- 4430
Global Website	<a href="http://www.duracell.com">www.duracell.com</a>
Consumer Relations: NA	North America: 1-800-551-2355 (9:00 AM - 5:00 PM EST)
Consumer Relations: E&A	(UK) 0800 716434, (FR) 0800 346 790 Service & appel gratuits, (IRL) 1 800 509 176, (DE) 800 101 2112, (AT) 0800 1025 1956, (CH) 0800 000 885, (BE) 0800 509 95, (NL) 0800 265 8616, (IT) 800 125 662, (ES) 900 800 522, (PT) 800 781 012, (GR) 210 66 75 000, (CY) 22-210900, (DK-SE-FI-NO) 4687991926, (ZA) +27211403500, (RO) 021 3361915, (MD) 022472402, (BG) 02 40 24 500, (BIH) 033756000, (MNE) 020261920, (PL) 22 692 42 77, (LT) (8) 37 401 111, (LV) 67798667, (IS) 3545222700, (EE) +3726505555, (CZ) +420233332010, (SK) +42153419601, (HU) 0620 770 7099, (HR) 0800 0009, (SI) 01/588 6800, (AZ) 812 3100949, (UA) +380444909771 (ДП «CAB 92») & +380442476704 (TOB «IHBECTKOM»), (KZ) +7 727 250 05 50, (TM) 00865 530070, (KG) 0312 41 77 04 (Apple City International), (TR) 0 850 502 61 40.
3. Article Information	
Description	Duracell branded consumer zinc air button cell battery
Product Category	Electro-technical device
Use	Portable power source for electronic devices
Global sub-brands (Retail)	Duracell
Sizes	10, 13, 312, 675
IEC Designation	PR70 (10), PR48 (13), PR41 (312), PR44 (675)
Principles of Operation	A battery powers a device by converting stored chemical energy into electrical energy.


## Article Information Sheet (AIS)

Representative Product Image	 A Duracell 312 battery pack, model 312, featuring the Duracell logo and "#1 TRUSTED BRAND" claim. The pack contains 8 batteries and is labeled "8 BATTERIES".
<b>4. Article Construction</b>	
Applicable Battery Industry Standards	ANSI C18.1M Part 1, ANSI C18.1M Part 2, ANSI C18.4, IEC 60086-1, IEC 60086-2, IEC 60086-5. Button cells exempt from any IEC 60086-5 testing.
Electro-technical System	Zinc air
Anode (Electrode - Negative)	Zinc (CAS # 7440-66-6)
Cathode (Electrode - Positive)	Air (Oxygen)
Electrolyte	Alkali Metal Hydroxide (Aqueous Mixture: potassium hydroxide - CAS # 1310-58-3; sodium hydroxide - CAS # 1310-73-2)
Materials of Construction - Can	Nickel plated steel
Declarable Substances (IEC 62474 Criteria 1)	Lead 0.01 - 0.06% (see Section 10 - EU Battery Directive)
Mercury Free Battery (ANSI C18.4M <5ppm)	Yes
Small Cell or Battery (ANSI C18.1M Part 2; IEC 60086-5)	All sizes of button cell batteries fit inside a specially designed test cylinder 2.25 inches (57.1mm) long by 1.25 inches (31.70 mm) wide.
<b>5. Health &amp; Safety</b>	
Ingestion/Small Parts Warning	<u>Required for sizes of button cell batteries:</u> Keep away from children. If swallowed, consult a physician immediately.
Normal Conditions of Use	Exposure to contents inside the sealed battery will not occur unless the battery leaks, is exposed to high temperatures, or is mechanically abused.
Note to Physician	A damaged battery will release concentrated and caustic potassium hydroxide.
First Aid - If swallowed	Do not induce vomiting. Seek medical attention immediately. For information on treatment, call 24 HOUR BATTERY INGESTION HOTLINE (telephone number below).
Poison Center/North America	<b>USA/CANADA CALLS ONLY: 1-800-498-8666 (toll-free) 24-HOUR BATTERY INGESTION HOTLINE</b>
Poison Centers/World Directory	<a href="http://globalcrisis.info/poisonemergency.html#AAA">http://globalcrisis.info/poisonemergency.html#AAA</a>
First Aid - Eye Contact	Flush with water for at least 15 minutes. Seek medical care if irritation persists.
First Aid - Skin Contact	Remove contaminated clothing. Wash skin with soap and water. Seek medical care if irritation persists.
First Aid - Inhalation	Remove to fresh air.

## Article Information Sheet (AIS)

<b>Precautionary Statements</b>	<b>CAUTION:</b> Keep batteries away from children. If swallowed, consult a physician at once. Batteries can explode or leak if heated, disassembled, shorted, recharged, exposed to fire or high temperature or inserted incorrectly. Do not carry batteries loose in your pocket or purse.
<b>6. Fire Hazard &amp; Firefighting</b>	
<b>Fire Hazard</b>	Batteries may rupture or leak if involved in a fire.
<b>Extinguishing Media</b>	Use any extinguishing media appropriate for the surrounding area.
<b>Fires Involving Large Quantities of Batteries</b>	Large quantities of batteries involved in a fire will rupture and release caustic potassium hydroxide. Firefighters should wear self-contained breathing apparatus and protective clothing.
<b>7. Handling &amp; Storage</b>	
<b>Handling Precautions</b>	Avoid mechanical and electrical abuse. Do not short circuit or install incorrectly. Batteries may rupture or vent if disassembled, crushed, recharged or exposed to high temperatures. Install batteries in accordance with equipment instructions.
<b>Storage Precautions</b>	Store batteries in a dry place at normal room temperature. Refrigeration does not make them last longer.
<b>Spills of Large Quantities of Loose Batteries (unpackaged)</b>	Notify spill personnel of large spills. Irritating and flammable vapors may be released from leaking or ruptured batteries. Spread batteries apart to stop shorting. Eliminate all ignition sources. Evacuate area and allow vapors to dissipate. Clean-up personnel should wear appropriate PPE to avoid eye and skin contact and inhalation of vapors or fumes. Increase ventilation. Carefully collect batteries and place in appropriate container for disposal. Remove any spilled liquid with absorbent material and contain for disposal.
<b>8. Disposal Considerations (GHS Section 13)</b>	
<b>Collection &amp; Proper Disposal</b>	Dispose of used (or excess) batteries in compliance with federal, state/provincial and local regulations. Do not accumulate large quantities of used batteries for disposal as accumulations could cause batteries to short-circuit. Do not incinerate. In countries, such as Canada and the EU, where there are regulations for the collection and recycling of batteries, consumers should dispose of their used batteries into the collection network at municipal depots and retailers. They should not dispose of batteries with household trash.
<b>USA EPA RCRA (40 CFR 261)</b>	Classified as non-hazardous waste (not ignitable, corrosive, reactive or toxic). Federal Universal Waste Regulations (40 CFR 273) do not apply. State requirements may be more stringent than Federal.
<b>California Universal Waste Rule (Cal. Code Regs. Title 22, Div. 4.5, Ch. 23)</b>	California prohibits disposal of batteries as trash (including household trash).
<b>Vermont Primary Battery Stewardship Law (ACT 139)</b>	In Vermont, consumers must recycle zinc air batteries. For information, contact <a href="http://www.call2recycle.org">http://www.call2recycle.org</a>
<b>9. Transport Information (GHS Section 14)</b>	

## Article Information Sheet (AIS)

<b>Regulatory Status</b>	Not regulated. Zinc air batteries (sometimes referred to as “Dry Cell” or “household” batteries) are not listed or regulated as dangerous goods under IATA Dangerous Goods Regulations, ICAO Technical Instructions, IMDG Code, UN Model Regulations, U.S. Hazardous Materials Regulations (49 CFR), and UNECE ADR.
<b>UN Identification Number/ Shipping Name</b>	None - Not Required
<b>Special Provision (SP) Conformance</b>	Special regulatory provisions require batteries to be packaged in a manner that prevents the generation of a dangerous quantity of heat and short circuits. Shippers can prepare batteries by taping the terminals, individually packaging batteries, or otherwise segregating the batteries to prevent risk of creating a short circuit. Batteries shipped in original unopened Duracell packaging is compliant.
<b>US DOT SP</b>	49 CFR 172.102 Special Provision 130
<b>Air Transport (IATA/ICAO) SP</b>	Special Provision A123 (IATA 62nd Edition - 2021). NOTE: The words "NOT RESTRICTED" and "SPECIAL PROVISION A123" must be included on the description of the substance on the Air Waybill, when air way-bill is issued.
<b>Passenger Air Travel</b>	No restrictions
<b>Emergency Transportation Hotline</b>	<b>CHEMTREC 24-Hour Emergency Response Hotline</b> <b>Within the United States call +703-527-3887</b> <b>Outside the United States, call +1 703-527-3887 (Collect)</b>
<b>10. Regulatory Information (GHS Section 15)</b>	
<b>10a. Battery Requirements</b>	
<b>USA EPA Mercury Containing &amp; Rechargeable Battery Management Act of 1996</b>	During the manufacturing process, no mercury is added.
<b>EU Battery Directive 2006/66/EC &amp; amendment 2013/56/EU</b>	Compliant with marking and substance EU Battery Directive restrictions for mercury (<0.0005%); cadmium (<0.0020%) and lead (<0.0040%). The concentration of lead in the zinc/air cells is between 100ppm to 600ppm (0.01% to 0.06%). Due to the size of the batteries, the marking is allowed to be printed on the packaging. A specimen of the marking is shown on the right: 
<b>10b. General Requirements</b>	
<b>USA CPSIA 2008 (PL 11900314)</b>	Exempt
<b>USA CPSC FHSA (16 CFR 1500)</b>	Consumer batteries are not listed as a hazardous product.
<b>USA EPA TSCA Section 13 (40 CFR 707.20)</b>	For customs clearance purpose, batteries are defined as an "Article".
<b>USA EPA RCRA (40 CFR 261)</b>	Classified as non-hazardous waste (not ignitable, corrosive, reactive or toxic). Federal Universal Waste Regulations (40 CFR 273) do not apply. State requirements may be more stringent than Federal.
<b>California Prop 65</b>	No warning required per 3rd party assessment.
<b>CANADA Products Containing Mercury Regulations SOR/20140254</b>	Mercury free
<b>EU REACH REGULATION (EC) NO. 1907/2006</b>	Regulated as an “article.” No listed substances are present (>0.1% w/w) in accordance with ECJ article definition of 10 September 2015.

## Article Information Sheet (AIS)

EU REACH Article 31	SDS is not required consumer alkaline batteries.
German Federal Water Management Act (WHG)	Not applicable - primary zinc air batteries are articles.
<b>10c. Regulatory Definitions - Articles</b>	
USA OSHA	29 CFR 1910.1200(b)(6)(v)
USA TSCA	40 CFR 704.3; 710.2(3)(c); and [19 CFR 12.1209a]]
EU REACH	Title 1 - Chapter 2 - Article 3(3)
GHS	Section 1.3.2.1
<b>11. Other Information</b>	
<b>11a. AIS Hazard Communication Approaches (consulted in developing this document):</b>	
Globally Harmonized System (GHS)	GHS SDS requirements and classification criteria do not apply to articles or products (such as batteries) that have a fixed shape, which are not intended to release a chemical. The article exemption is found in Section 1.3.2.1.1 of the GHS and reads: <i><b>The GHS applies to pure substances and their dilute solutions and to mixtures. "Articles" as defined by the Hazard Communication Standard (29 CFR 1900.1200) of the OSHA of the USA, or by similar definition, are outside the scope of the system.</b></i>
Joint Article Management Promotion Consortium JAMP	JAMP is a Japanese Industry Association who developed the concept of an Article Information Sheet as a supply chain tool to share and communicate chemical information in articles. The AIS authoring process is based on "declarable" substances to meet global regulatory requirements as well as substances to be reported by GADSL, JIG, etc.
IEC 62474 Ed. 1.0 B:2012 Material Declaration for Products of and for the Electro-technical Industry	An international standard that came into effect in March 2012 concerning declaration for electrical and electronic products. IEC 6274 replaces the defunct Joint Industry Guide – Material Declaration for Electro-technical Products (JIG-101-Ed 4.1 (May 21, 2012)
IEC 62474 Database - Publically available online (maintained by TC11: Environmental Standardization for electrical and electronic products and systems.	The general principle for a substance to be included in the database as a declarable substance is: 1) existing national laws or regulations in an IEC member country that are relevant to Electro-technical products and that prohibit or restrict substances, or that have a labeling, communication, reporting or notification requirement, and 2) applying IEC 62474 criteria results in identification of declarable substance.
ANSI Z 400.1/Z19.1 (2010)	2.1 Scope: Applies to preparation of SDSs for hazardous chemicals used under occupational conditions. Does not address how the standard may be applied to articles. It presents basic information on how to develop and write a SDS. Additional information is provided to help comply with state and federal environmental and safety laws and regulations. Elements of the standard may be acceptable for International use.
ANSI C18.4M-2017 Portable Cells and Batteries - Environmental	This standard provides regulatory guidance and a template to author an article information sheet for a portable consumer battery. See Annex C.2 (Informational) Safety Data Sheets and Annex E (Informational) Article Information Sheet.

## Article Information Sheet (AIS)

**DISCLAIMER:** This AIS is intended to provide a brief summary of our knowledge and guidance regarding the use of this material. The information contained here has been compiled from sources considered by Duracell to be dependable and is accurate to the best of the Company's knowledge. It is not meant to be an all-inclusive document on worldwide hazard communication regulations. This information is offered in good faith. Each user of this material needs to evaluate the conditions of use and design the appropriate protective mechanisms to prevent employee exposures, property damage or release to the environment. Duracell assumes no responsibility for injury to the recipient or third persons or for any damage to any property resulting from misuse of the product.